



ELECTRONICS, INC.
44 FARRAND STREET
BLOOMFIELD, NJ 07003
(973) 748-5089
<http://www.nteinc.com>

NTE2418 (NPN) & NTE2419 (PNP) Silicon Complementary Transistors Digital w/2 Built-In Bias 47k Resistors (Surface Mount)

Features:

- Built-In Bias Resistors
- Small SOT-23 Surface Mount Package

Applications:

- Switching Circuits
- Inverters
- Interface Circuits
- Driver

Absolute Maximum Ratings: ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Collector-Base Voltage, V_{CBO}	50V
Collector-Emitter Voltage, V_{CEO}	50V
Emitter-Base Voltage, V_{EBO}	10V
Collector Current, I_C	
Continuous	100mA
Peak	200mA
Collector Dissipation, P_C	200mW
Operating Junction Temperature, T_J	+150°C
Storage Temperature Range, T_{stg}	-55° to +150°C

Note 1. NTE2418 is a **discontinued** device and **no longer available**.

Electrical Characteristics: ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Collector Cutoff Current	I_{CBO}	$V_{CB} = 40\text{V}$, $I_E = 0$	-	-	0.1	μA
	I_{CEO}	$V_{CE} = 40\text{V}$, $I_B = 0$	-	-	0.5	μA
Emitter Cutoff Current	I_{EBO}	$V_{EB} = 5\text{V}$, $I_C = 0$	30	53	80	μA
DC Current Gain	h_{FE}	$V_{CE} = 5\text{V}$, $I_C = 10\text{mA}$	50	-	-	
Collector-Base Breakdown Voltage	$V_{(BR)CBO}$	$I_C = 10\mu\text{A}$, $I_E = 0$	50	-	-	V
Collector-Emitter Breakdown Voltage	$V_{(BR)CBO}$	$I_C = 100\mu\text{A}$, $R_{BE} = \infty$	50	-	-	V
Collector-Emitter Saturation Voltage	$V_{CE(\text{sat})}$	$I_C = 5\text{mA}$, $I_B = 0.25\text{mA}$	-	0.1	0.3	V
Current Gain-Bandwidth Product NTE2418	f_T	$V_{CE} = 10\text{V}$, $I_C = 5\text{mA}$	-	250	-	MHz
NTE2419			-	200	-	MHz

Electrical Characteristics (Cont'd): ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Output Capacitance NTE2418	C_{ob}	$V_{CB} = 10\text{V}$, $f = 1\text{MHz}$	-	3.5	-	pF
NTE2419			-	5.3	-	pF
Input OFF Voltage	$V_{I(\text{off})}$	$V_{CE} = 5\text{V}$, $I_C = 100\mu\text{A}$	0.8	1.1	1.5	V
Input ON Voltage	$V_{I(\text{on})}$	$V_{CE} = 0.2\text{V}$, $I_C = 10\text{mA}$	1.0	2.5	5.0	V
Input Resistance	R_1		32	47	62	k Ω
Input Resistance Ratio	R_1/R_2		0.9	1.0	1.1	

