



## MMIC VCO w/ HALF FREQUENCY OUTPUT & DIVIDE-BY-4, 10.43 - 11.46 GHz

### Typical Applications


Low noise MMIC VCO w/Half Frequency, Divide-by-4 Outputs for:

- VSAT Radio
- Point to Point/Multipoint Radio
- Test Equipment & Industrial Controls
- Military End-Use

### Features

- Dual Output:  $F_o = 10.43 - 11.46$  GHz  
 $F_o/2 = 5.215 - 5.73$  GHz
- Pout: +7 dBm
- Phase Noise: -110 dBc/Hz @100 KHz Typ.
- No External Resonator Needed
- 32 Lead 5x5mm SMT Package: 25mm<sup>2</sup>

### Functional Diagram



### General Description

The HMC513LP5 & HMC513LP5E are GaAs InGaP Heterojunction Bipolar Transistor (HBT) MMIC VCOs. The HMC513LP5 & HMC513LP5E integrate resonators, negative resistance devices, varactor diodes and feature half frequency and divide-by-4 outputs. The VCO's phase noise performance is excellent over temperature, shock, and process due to the oscillator's monolithic structure. Power output is +7 dBm typical from a +3V supply voltage. The prescaler function can be disabled to conserve current if not required. The voltage controlled oscillator is packaged in a leadless QFN 5x5 mm surface mount package, and requires no external matching components.

### Electrical Specifications, $T_A = +25^\circ C$ , $V_{cc1}, V_{cc2} = +3V$

| Parameter  | Min.                        | Typ.                          | Max.                 | Units                    |    |
|--|-----------------------------|-------------------------------|----------------------|--------------------------|----|
| Frequency Range  | $F_o$<br>$F_o/2$            | 10.43 - 11.46<br>5.215 - 5.73 |                      | GHz<br>GHz               |    |
| Power Output   | RFOUT<br>RFOUT/2<br>RFOUT/4 | +5<br>+5<br>-10               | +10<br>+11<br>-4     | dBm<br>dBm<br>dBm        |    |
| SSB Phase Noise @ 100 kHz Offset, $V_{tune} = +5V @ RFOUT$ |                             | -110                          |                      | dBc/Hz                   |    |
| Tune Voltage   | $V_{tune}$                  | 2                             | 13                   | V                        |    |
| Supply Current   | $I_{cc1} \& I_{cc2}$        | 240                           | 275                  | 290                      | mA |
| Tune Port Leakage Current ( $V_{tune} = 13V$ )             |                             |                               | 10                   | $\mu A$                  |    |
| Output Return Loss   |                             | 2                             |                      | dB                       |    |
| Harmonics/Subharmonics                                     | 1/2<br>3/2<br>2nd<br>3rd    |                               | 32<br>26<br>15<br>28 | dBc<br>dBc<br>dBc<br>dBc |    |
| Pulling (into a 2.0:1 VSWR)                                |                             |                               | 5                    | MHz pp                   |    |
| Pushing @ $V_{tune} = 5V$                                  |                             |                               | 25                   | MHz/V                    |    |
| Frequency Drift Rate                                       |                             |                               | 1                    | MHz/ $^\circ C$          |    |


Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.

For price, delivery, and to place orders: Analog Devices, Inc., One Technology Way, P.O. Box 9106, Norwood, MA 02062-9106  
Phone: 781-329-4700 • Order online at [www.analog.com](http://www.analog.com)  
Application Support: Phone: 1-800-ANALOG-D




**MMIC VCO w/ HALF FREQUENCY OUTPUT & DIVIDE-BY-4, 10.43 - 11.46 GHz**


**Frequency vs. Tuning Voltage, T= 25°C**




**Frequency vs. Tuning Voltage, Vcc= +3V**




**Sensitivity vs. Tuning Voltage, Vcc= +3V**




**Output Power vs. Tuning Voltage, Vcc= +3V**



**SSB Phase Noise vs. Tuning Voltage**



**SSB Phase Noise @ Vtune= +5V**




Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.

For price, delivery, and to place orders: Analog Devices, Inc., One Technology Way, P.O. Box 9106, Norwood, MA 02062-9106 Phone: 781-329-4700 • Order online at [www.analog.com](http://www.analog.com) Application Support: Phone: 1-800-ANALOG-D




## MMIC VCO w/ HALF FREQUENCY OUTPUT & DIVIDE-BY-4, 10.43 - 11.46 GHz


**RFOUT/2 Frequency vs. Tuning Voltage, Vcc= +3V**




**RFOUT/2 Output Power vs. Tuning Voltage, Vcc= +3V**



**Divide-by-4 Frequency vs. Tuning Voltage, Vcc= +3V**



**Divide-by-4 Output Power vs. Tuning Voltage, Vcc= +3V**



### Absolute Maximum Ratings

|  |                |
|--|----------------|
| Vcc1, Vcc2   | +3.5 Vdc       |
| Vtune  | 0 to +15V      |
| Junction Temperature   | 135 °C         |
| Continuous P <sub>diss</sub> (T=85 °C)<br>(derate 27 mW/C above 85 °C) | 1.3 W          |
| Thermal Resistance<br>(junction to ground paddle)                      | 37.5 °C/W      |
| Storage Temperature  | -65 to +150 °C |
| Operating Temperature  | -40 to +85 °C  |

### Typical Supply Current vs. Vcc

| Vcc (V) | I <sub>cc</sub> (mA) |
|---------|----------------------|
| 2.75    | 230                  |
| 3.0     | 275                  |
| 3.25    | 320                  |

Note: VCO will operate over full voltage range shown above.




**ELECTROSTATIC SENSITIVE DEVICE  
OBSERVE HANDLING PRECAUTIONS**



## MMIC VCO w/ HALF FREQUENCY OUTPUT & DIVIDE-BY-4, 10.43 - 11.46 GHz

### Outline Drawing



**NOTES:**

1. LEADFRAME MATERIAL: COPPER ALLOY
2. DIMENSIONS ARE IN INCHES [MILLIMETERS]
3. LEAD SPACING TOLERANCE IS NON-CUMULATIVE.
4. PAD BURR LENGTH SHALL BE 0.15mm MAXIMUM.  
PAD BURR HEIGHT SHALL BE 0.05mm MAXIMUM.
5. PACKAGE WARP SHALL NOT EXCEED 0.05mm.
6. ALL GROUND LEADS AND GROUND PADDLE MUST BE SOLDERED TO PCB RF GROUND.
7. REFER TO HITTITE APPLICATION NOTE FOR SUGGESTED LAND PATTERN.

### Package Information

| Part Number | Package Body Material                              | Lead Finish   | MSL Rating          | Package Marking <sup>[3]</sup> |
|-------------|--|---------------|---------------------|--------------------------------|
| HMC513LP5   | Low Stress Injection Molded Plastic                | Sn/Pb Solder  | MSL3 <sup>[1]</sup> | H513<br>XXXX                   |
| HMC513LP5E  | RoHS-compliant Low Stress Injection Molded Plastic | 100% matte Sn | MSL3 <sup>[2]</sup> | H513<br>XXXX                   |

[1] Max peak reflow temperature of 235 °C  
 [2] Max peak reflow temperature of 260 °C  
 [3] 4-Digit lot number XXXX

### Pin Descriptions

| Pin Number                                   | Function | Description   | Interface Schematic |
|--|----------|---|---------------------|
| 1 - 3, 7 - 10, 13 - 18, 20, 22 - 28, 30 - 32 | N/C      | No Connection. These pins may be connected to RF/DC ground. Performance will not be affected.                       |                     |
| 4  | RFOUT/4  | Divide-by-4 Output  |                     |
| 6  | VCC1     | Supply Voltage for prescaler. If prescaler is not required, this pin may be left open to conserve 40 mA of current. |                     |

Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.

For price, delivery, and to place orders: Analog Devices, Inc., One Technology Way, P.O. Box 9106, Norwood, MA 02062-9106  
 Phone: 781-329-4700 • Order online at [www.analog.com](http://www.analog.com)  
 Application Support: Phone: 1-800-ANALOG-D




## MMIC VCO w/ HALF FREQUENCY OUTPUT & DIVIDE-BY-4, 10.43 - 11.46 GHz

### Pin Descriptions

| Pin Number    | Function | Description   | Interface Schematic |
|---------------|----------|---|---------------------|
| 12            | RFOUT/2  | Half frequency output (AC coupled).   |                     |
| 19            | RFOUT    | RF output (AC coupled).   |                     |
| 21            | VCC2     | Supply Voltage, +3V   |                     |
| 29            | VTUNE    | Control Voltage Input. Modulation port bandwidth dependent on drive source impedance. |                     |
| 5, 11, Paddle | GND      | Package bottom has an exposed metal paddle that must be connected to RF/DC ground.    |                     |

### Typical Application Circuit




Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.

For price, delivery, and to place orders: Analog Devices, Inc., One Technology Way, P.O. Box 9106, Norwood, MA 02062-9106 Phone: 781-329-4700 • Order online at [www.analog.com](http://www.analog.com) Application Support: Phone: 1-800-ANALOG-D

## MMIC VCO w/ HALF FREQUENCY OUTPUT & DIVIDE-BY-4, 10.43 - 11.46 GHz



### Evaluation PCB



### List of Materials for Evaluation PCB 110227 [1]

| Item    | Description                    |
|---------|--------------------------------|
| J1 - J4 | PCB Mount SMA RF Connector     |
| J5 - J6 | 2 mm DC Header                 |
| C1 - C3 | 100 pF Capacitor, 0402 Pkg.    |
| C4      | 1,000 pF Capacitor, 0402 Pkg.  |
| C5 - C7 | 2.2 $\mu$ F Tantalum Capacitor |
| U1      | HMC513LP5(E) VCO               |
| PCB [2] | 110225 Eval Board              |

[1] Reference this number when ordering complete evaluation PCB

[2] Circuit Board Material: Arlon 25FR

The circuit board used in the final application should use RF circuit design techniques. Signal lines should have 50 Ohm impedance while the package ground leads and backside ground paddle should be connected directly to the ground plane similar to that shown. A sufficient number of via holes should be used to connect the top and bottom ground planes. The evaluation circuit board shown is available from Hittite upon request.