

245 Series Shock-Safe Fuse Holders for 2AG Fuses



 \cap

.020"

SOLDER TERMINAL PART NO. 245001

Dimensions



+.005' - .000'

.438" +.005 - .000

MOUNTING HOLE

.390"



.048" DIA.

NEMA Q.C. TERMINAL PART NO. 245002

.066"

TERMINAL DETAIL

Electrical	Rated at 10 amperes for any voltage up to 300 volts. Insulation Resistance: 10,000 megohm minimum at 500 VDC. Contact Resistance: Less than .005 ohm average at currents up to 1 ampere.		
Dielectric Strength	4000 volts terminal to panel, 3000 volts terminal to terminal. Mounting: Withstands 10 lbin. mounting torque. Maximum panel thickness is 250".		
Molded Parts	Body, knob, and hex nut material: Black, glass reinforced thermoplastic.		
Knob	Screwdriver slot, fuse extractor type with nickel- plated, beryllium copper insert. Stainless steel spring.		
Terminals	Brass. Tin-plated. Solder/Q.C. Terminals accept soldered wire or a .110" quick-connect receptacle. The NEMA-style .110" Q.C. terminal has a .048" hole.		
Ambient Temperature*	-40°C to +85°C.		

shock.

225 Series, 229 Series, 2200029 Series

Screwdriver slot knob style provides low profile

Shock-safe design reduces possibility of electrical

Product Characteristics

Compatible Fuse

Size

Features

* - Refer to Fuseology for information on proper fuseholder re-rating.

Agency Approvals				
Agency	Agency File Number			
91	E14721			
(fr)	7316			

Resources

Additional Information





RoHS 🔊 🗣

Ordering Information

Ordering Number	Catalog Number	Type of Terminal	Packaging	
02450001H	245001	Solder/Q.C. Terminal	Bulk 100 pieces	
02450001X	245001	Solder/Q.C. Terminal	Bulk 100 pieces	
02450002H	245002	NEMA Q.C. Terminal	Bulk 100 pieces	
02450002X	245002	NEMA Q.C. Terminal	Bulk 100 pieces	

Note: Part number 02450002 can be supplied with lockwasher or neoprene washer, or both.

Add to the end of part number a "L" for lockwasher and "N" for neophrene washer or "LN" for both.

Disclaimer Notice - Information furnished is believed to be accurate and reliable. However, users should independently evaluate the suitability of and test each product selected for their own applications. Littelfuse products are not designed for, and may not be used in, all applications. Read complete Disclaimer Notice at: www.littelfuse.com/disclaimer-electronics.