# HMC1051

### 8Vpp Optical Modulator Driver / Wideband Amplifier, DC - 30 GHz

	<b>Product Details</b>	Quality & Reliability	Life Cycle Status	
No Image Available	Request Data Sheet ECCN: EAR99	Waffle-Pak & Gel-Pak	Production,	
		Press & Media	Recommended for	
		Featured Article	New Designs	

Data Rate (Gbps)	Function	Gain (dB)	Group Delay Variation (ps)	Additive Jitter (ps)	Output Voltage Max. (Vp-p)	Package
32	8Vpp Optical Modulator Driver, with Peak Detect	16	±5	0.3	8	Chip

• Up to 32Gbps optical modulator driver • Test and Measurement Instrumentation

**Typical Applications** 

Microwave Radio & VSAT

• Military & Space

#### Features

- Low DC Power Dissipation, 1.05W for 8Vpp swing @ 6V supply
- Integrated peak-detect function
- 16 dB Gain @ 16 GHz
- +22 dBm saturated output power (8.0 Vpp)
- Low Additive RMS Jitter, <300 fsec
- Rise and Fall Times 11.5 psec
- Small Die Size:
  - 1.71 x 1.35 x 0.10 mm

## **General Description**

The HMC1051 is a GaAs MMIC PHEMT Distributed Amplifier die which operates between DC and 30 GHz. The amplifier provides 16 dB of gain, and + 20 dBm of output power at 1 dB gain compression. HMC1051 has a wide supply (Vdd) operating range from +5V to +7V.

Integrated Peak-Detect Function enables the output power stability for calibration and field monitoring. The HMC1051 amplifier I/Os are internally matched to 50 Ohms facilitating integration into Mutli-Chip-Modules (MCMs).

8.0Vpp output voltage swing can be obtained with 1250mVpp input when stimulated with 32Gbps 231-1 PRBS NRZ data.

The HMC1051 is suitable for a variety of wideband electronic warfare systems and test & measurement applications including NRZ applications up to 32 Gbps. The HMC1051 is capable of driving Mach-Zehnder optical modulator with electrical NRZ data.

Hittite Microwave (Chelmsford, MA USA) is an ISO 9001:2008 and AS9100:2009 Certified Designer and Manufacturer © 2000 - 2014 Hittite Microwave Corporation | Legal Notice | Privacy Policy 978-250-3343 | sales@hittite.com

#### **Functional Diagram**

