

Ph. 480-503-4295 | NOPP@FocusLCDs.com

# TFT | OLED | GRAPHIC | CHARACTER | UWVD | SEGMENT | CUSTOM

# Graphic OLED Module

Part Number O9696A-F-TW3

## Overview:

- 96x96 Graphic OLED
- Full Pixel Color
- Overall Size: 25.90mm x 30.10mm
- Parallel Interface

- -40C to 70C Operating Temperature
- 2.8V
- Controller: SEPS114A
- RoHS Compliant



## **Graphic OLED Features:**

Resolution: 96 x 96 Interface: Parallel Controller: SEPS114A


**RoHS Compliant** 

General Information Items	Specification  Main Panel	Unit	Note
Viewing Area	21.852 x 21.852	mm	-
Pixel Color	Full	-	-
Viewing Direction	Full	-	-
Voltage	2.8	V	-
Resolution	96x96	-	-
Controller IC	SEPS114A	-	-
Interface	Parallel	-	-
Operating temperature	-40 <b>~</b> +70	°C	-
Storage temperature	-40 <b>~</b> +85	°C	-

## **Mechanical Information**

	Item	Min	Тур.	Max	Unit	Note
Module size	X (Width)	-	25.90	-	mm	-
	Y (Height)	-	30.10	-	mm	-
0.20	Z (Depth)	-	-	1.30	mm	-

## 1. Outline Dimensions



3



## 2. Input Terminal Pin Assignment

NO.	Symbol	Description	1/0
1 & 34	NC	Power Supply Ground/ No Connection	-
2	VSSH	Ground of OEL Panel	Р
3	VCC_R	Voltage Output High Level for Scan Signal	Р
4	vcc_c	Power Supply for OEL Panel	Р
5	VDDR	Power Supply for Core Logic Circuit	Р
6	VDD	Power Supply for Operation	Р
7	PSEL	Regulator Enable/Disable for Logic Power Supply	I
8	VDDIO	Power Supply for I/O Pin	Р
9	RSTB	Power Reset for Controller and Driver	I
10	WRB	Write or Read/Write Select	I
11	RDB	Read or Read/Write Enable	I
12	CSB	Chip Select	I
13	A0	Data/Command Control	I
14-21	D0 – D7	Host Data Input/Output Bus  PS Description  O D[0] SCL: Synchronous Clock Input D[1] SDI: Serial Data Input D[2] SDO: Serial Data Outpu D[3] R/W: Serial Read (High)/Write (Low)  1 8-bit Bus: D[7:0]	I/O
22	PS	Select Parallel/ Serial Interface Type	I
23	C80	Select the CPU Type	I
24	OSC1	Fine Adjustment for Oscillation	I
25	OSC2	Fine Adjustment for Oscillation	0
26	IREF	Current Reference For Brightness Adjustment	1/0
27	VSS	Ground of Logic Circuit	Р
28	BPRE	External Voltage Reference for Pre-charge Signal	1/0
29	GPRE	External Voltage Reference for Pre-charge Signal	I/O
30	RPRE	External Voltage Reference for Pre-charge Signal	1/0
31	vcc_c	Power Supply for OEL Panel	Р
32	VCC_R	Voltage Output High Level for Scan Signal	Р
33	VSSH	Ground of OEL Panel	Р

I: Input, O: Output, P: Power



## 3. Optical Characteristics

ltem	Symbol	Condition	Min	Тур.	Max	Unit
Contrast Ratio	CR	$V_{DD} = 2.8V$ $V_{CC\_C} = 12.0V$		10000:1		-
	CIE (\A/bito)	Х	0.26	0.30	0.34	
	CIE (White)	Υ	0.29	0.33	0.37	
	CIE (Bod)	Χ	0.60	0.64	0.68	
Book Emission Wavelength	CIE (Red)	Υ	0.30	0.34	0.38	
Peak Emission Wavelength	CIE (Green)	Χ	0.27	0.31	0.35	-
		Υ	0.58	0.62	0.66	
	CIE (Blue)	X	0.10	0.14	0.18	
	CIL (Blue)	Υ	0.12	0.16	0.20	
Brightness	L <sub>br</sub>	-	80	100	-	Cd/m <sup>2</sup>
Viewing Angle		CR≥10000:1	Free		degree	

## 4. DC Electrical Characteristics

Characteristics	Symbol	Conditions	Min	Тур.	Max	Unit
Supply Voltage for Operation	V <sub>DD</sub>	-	2.4	2.8	3.3	V
Supply Voltage for I/O Pins	V <sub>DDIO</sub>	-	1.65	2.8	$V_{DD}$	V
Supply Voltage for Display	V <sub>cc_c</sub>	-	11.5	12.0	12.5	V
High Level Input	V <sub>IH</sub>	-	0.8V <sub>DDIO</sub>	-	V <sub>DDIO</sub>	V
Low Level Input	V <sub>IL</sub>	-	0	-	0.4	V
High Level Output	V <sub>OH</sub>	I <sub>OH</sub> = -0.1mA	V <sub>DDIO</sub> -0.4	-	-	٧
Low Level Output	V <sub>OL</sub>	I <sub>OL</sub> = -0.1mA	-	-	0.4	V
Operating Current for V <sub>DD</sub>	I <sub>DD</sub>	-	-	1.5	3.5	mA
Operating Current for V <sub>CC_C</sub>	I <sub>CC_C</sub>	-	-	19.2	24.0	mA
Sleep Mode Current for V <sub>DD</sub>	I <sub>DD, SLEEP</sub>	-	-	3	5	μΑ
Sleep Mode Current for V <sub>CC_C</sub>	I <sub>CC_C</sub> , SLEEP	-	-	2	10	μΑ


NOTE: If the maximum rating of the above parameters is exceeded, even momentarily, the quality of the product may be degraded. The maximum ratings specify the values which the product may be physically damaged if exceeded. Be sure to use the product within the range of the specified parameters.




## 5. Timing Characteristics

## 5.1 68XX-Series MPU Parallel Interface Timing Characteristics

Parameter	Symbol	Min	Max	Unit	Port
Address Setup Time	t <sub>AH6</sub> (Read)	10	-	ns	
Address Setup Time	t <sub>AH6</sub> (Write)	5	-	ns	CCD
Address Hold Time	t <sub>AS6</sub> (Read)	10	-	ns	CSB
	t <sub>AS6</sub> (Write)	5	-	ns	RS
System Cycle Timing	t <sub>cyc6</sub>	200	-	ns	
Read "L" Pulse Width	t <sub>ELR6</sub>	90	-	ns	
Read "H" Pulse Width	t <sub>ELR6</sub>	90	-	ns	
System Cycle Timing	t <sub>cyc6</sub>	100	-	ns	E
Write "L" Pulse Width	t <sub>ELW6</sub>	45	-	ns	
Write "H" Pulse Width	t <sub>EHW6</sub>	45	-	ns	
Read Data Output Delay Time (*C <sub>L</sub> =15pF)	t <sub>RDD6</sub>	0	70	ns	
Data Hold Timing (*C <sub>L</sub> =15pF)	t <sub>RDH6</sub>	0	70	ns	_
Data Setup Timing	t <sub>DS6</sub>	40	-	ns	D[7:0]
Data Hold Timing	t <sub>DH6</sub>	10	-	ns	



( Read Timing )




6


( Write Timing )



#### **80XX-Series MPU Parallel Interface Timing Characteristics** 5.2

Parameter	Symbol	Min	Max	Unit	Port
Address Setup Timing	t <sub>AS8</sub>	5	-	ns	CSB
Address Hold Timing	t <sub>AH8</sub>	5	-	ns	A0
System Cycle Timing	t <sub>cyc8</sub>	200	-	ns	
Read "L" Pulse Width	t <sub>RDLR8</sub>	90	-	ns	RDB
Read "H" Pulse Width	t <sub>RDHR8</sub>	90	-	ns	
System Cycle Timing	t <sub>cyc8</sub>	100	-	ns	
Write "L" Pulse Width	t <sub>WRLW8</sub>	45	-	ns	WRB
Write "H" Pulse Width	t <sub>wrhw8</sub>	45	-	ns	
Read Data Output Delay Time (*C <sub>L</sub> =15pF)	t <sub>RDD8</sub>	-	60	ns	
Data Hold Timing (*C <sub>L</sub> =15pF)	t <sub>RDH8</sub>	0	60	ns	D[7:0]
Data Setup Timing	t <sub>DS8</sub>	30	-	ns	D[7.0]
Data Hold Timing	t <sub>DH8</sub>	10	-	ns	






( Write Timing )



## 5.3 Serial Interface Timing Characteristics

Parameter	Symbol	Min	Max	Unit	Port
Serial Clock Cycle	t <sub>CYCS</sub>	200	-	ns	
SCL "L" Pulse Width	t <sub>SLW</sub>	90	-	ns	SCL
SCL "H" Pulse Width	t <sub>SHW</sub>	90	-	ns	
Data Setup Timing	t <sub>DSS</sub>	25	-	ns	
Data Hold Timing	t <sub>DHS</sub>	25	-	ns	SDI
CSB-SCL Timing	t <sub>CSS</sub>	25	-	ns	
CSB-Hold Timing	t <sub>CSH</sub>	25	-	ns	CSB
RS-SCL Timing	t <sub>RSS</sub>	25	-	ns	
RS-Hold Timing	t <sub>RSH</sub>	25	-	ns	A0





## 6. Cautions and Handling Precautions

### 6.1 Handling and Operating the Module

- 1. When the module is assembled, it should be attached to the system firmly. Do not warp or twist the module during assembly work.
- 2. Protect the module from physical shock or any force. In addition to damage, this may cause improper operation or damage to the module and back-light unit.
- 3. Note that polarizer is very fragile and could be easily damaged. Do not press or scratch the surface.
- 4. Do not allow drops of water or chemicals to remain on the display surface. If you have the droplets for a long time, staining and discoloration may occur.
- 5. If the surface of the polarizer is dirty, clean it using some absorbent cotton or softcloth.
- 6. The desirable cleaners are water, IPA (Isopropyl Alcohol) or Hexane. Do not use ketene type materials (ex. Acetone), Ethyl alcohol, Toluene, Ethyl acid or Methyl chloride. It might permanent damage to the polarizer due to chemical reaction.
- 7. If the liquid crystal material leaks from the panel, it should be kept away from the eyes or mouth. In case of contact with hands, legs, or clothes, it must be washed away thoroughly with soap.
- 8. Protect the module from static, it may cause damage to the CMOS ICs.
- 9. Use finger-stalls with soft gloves in order to keep display clean during the incoming inspection and assembly process.
- 10. Do not disassemble the module.
- 11. Protection film for polarizer on the module shall be slowly peeled off just before use so that the electrostatic charge can be minimized.
- 12. Pins of I/F connector shall not be touched directly with bare hands.
- 13. Do not connect, disconnect the module in the "Power ON" condition.
- 14. Power supply should always be turned on/off by the item Power On Sequence & Power Off Sequence.

#### 6.2 Storage and Transportation

- 1. Do not leave the panel in high temperature, and high humidity for a long time. It is highly recommended to store the module with temperature from 0 to 35 °C and relative humidity of less than 70%
- 2. Do not store the OLED module in direct sunlight.
- 3. The module shall be stored in a dark place. When storing the modules for a long time, be sure to adopt effective measures for protecting the modules from strong ultraviolet radiation, sunlight, or fluorescent light.
- 4. It is recommended that the modules should be stored under a condition where no condensation is allowed. Formation of dewdrops may cause an abnormal operation or a failure of the module. In particular, the greatest possible care should be taken to prevent any module from being operated where condensation has occurred inside.
- 5. This panel has its circuitry FPC on the bottom side and should be handled carefully in order not to be stressed.