DC/DC Product Specification

- 1/8th brick fully regulated DCDC converter.

AVO120-48S12

1/8th brick

Input voltage: 36-75V Single Output: 12V Rated power: 120W

Special Features

-2:1 Wide input range

- -Optimised for High density, small space applications
- -Low ripple and noise
- -Fixed switching frequency
- -High efficiency
- -High capacitive load capability
- -Basic insulation system
- -Pre-bias start-up capability
- -Through hole or SMT termination
- Open frame structure with Base-plate option

Safety

- -UL, cUL: UL60950
- -TUV/CE: IEC/EN60950



Rev 09/07/2012 AVO120 series Page 1 of 2

Product Description

The AVO120-48S12 is the latest high efficiency 1/8th brick series. It operates from a wide input range of 36Vdc to 75Vdc and provides a regulated output voltage of 12Vdc. The output is rated to a power level up to 120Watts. Its protection features include Non-latching OCP, OTP and OVP. It also has an enable pin on the primary side of the converter. The unit is an open frame design with base-plate option that is optimised for either contact-cooled applications or forced airflow applications.

Specifications

Input specificationInput range36Vdc to 75VdcInput Surge100V for 100mSecControl specificationEnableTTL compatible Positive or Negative enableOutput specificationOutput voltage12Vdc.Trim range+10% to -20% VoutOutput Current10ARipple and noise50mV pk-pkRegulationLoad regulation =10mV, Line regulation = 5mVSwitching FrequencyFixed switching frequency 165KhzSolation Voltage2000Vdc100mV deviation 150uS recovery	Feature	
SafetyUL:UL60950TUV/CE:IEC/EN60950Input specificationInput range36Vdc to 75VdcInput Surge100V for 100mSecControl specificationEnableTTL compatible Positive or Negative enableOutput specificationOutput Voltage12Vdc.Trim range+10% to -20% VoutOutput Current10ARipple and noise50mV pk-pkLoad regulation =10mV, Line regulation = 5mVSwitching FrequencyFixed switching frequency 165KhzIsolation Voltage2000Vdc100mV deviation 150uS recovery	Super high efficiency: Functions:	93%(12V) Remote control, trim function, Sense; Input LVP, output OVP and OCP, OTP Open frame structure with base plate option.
UL:UL60950TUV/CE:IEC/EN60950Input specificationInput range36Vdc to 75VdcInput Surge100V for 100mSecControl specificationEnableTTL compatible Positive or Negative enableOutput specificationOutput voltage12Vdc.Trim range+10% to -20% VoutOutput Current10ARipple and noise50mV pk-pkLoad regulation= 5mVSwitching FrequencyFixed switching frequency 165KhzIsolation Voltage2000Vdc100mV deviation 150uS recovery		Basic Insulation
TUV/CE:IEC/EN60950Input specification36Vdc to 75VdcInput Surge100V for 100mSecControl specificationTTL compatible Positive or Negative enableOutput specification0utput specificationOutput Voltage12Vdc.Trim range+10% to -20% VoutOutput Current10ARipple and noise50mV pk-pkRegulationLoad regulation =10mV, Line regulation = 5mVSwitching FrequencyFixed switching frequency 165KhzIsolation Voltage2000Vdc100mV deviation 150uS recovery		
Input range36Vdc to 75VdcInput Surge100V for 100mSecControl specificationTTL compatible Positive or Negative enableOutput specificationTTL compatible Positive or Negative enableOutput specification12Vdc.Output Voltage12Vdc.Trim range+10% to -20% VoutOutput Current10ARipple and noise50mV pk-pkLoad regulationLoad regulation =10mV, Line regulation = 5mVSwitching FrequencyFixed switching frequency 165KhzIsolation Voltage2000Vdc100mV deviation 150uS recovery		
Input Surge100V for 100mSecControl specificationTTL compatible Positive or Negative enableEnableTTL compatible Positive or Negative enableOutput specification12Vdc.Output Voltage12Vdc.Trim range+10% to -20% VoutOutput Current10ARipple and noise50mV pk-pkRegulationLoad regulation =10mV, Line regulation = 5mVSwitching FrequencyFixed switching frequency 165KhzIsolation Voltage2000Vdc100mV deviation 150uS recovery	Input specification	
EnableTTL compatible Positive or Negative enableOutput specificationOutput Voltage12Vdc.Trim range+10% to -20% VoutOutput Current10ARipple and noise50mV pk-pkRegulationLoad regulation =10mV, Line regulation = 5mVSwitching FrequencyFixed switching frequency 165KhzIsolation Voltage2000Vdc100mV deviation 150uS recovery		
Output specificationOutput Voltage12Vdc.Trim range+10% to -20% VoutOutput Current10ARipple and noise50mV pk-pkLoad regulationLoad regulation =10mV, Line regulation = 5mVSwitching FrequencyFixed switching frequency 165KhzIsolation Voltage2000Vdc100mV deviation 150uS recovery	Control specification	
Output Voltage12Vdc.Trim range+10% to -20% VoutOutput Current10ARipple and noise50mV pk-pkRegulationLoad regulation =10mV, Line regulation = 5mVSwitching FrequencyFixed switching frequency 165KhzIsolation Voltage2000Vdc100mV deviation 150uS recovery	Enable	TTL compatible Positive or Negative enable
Trim range+10% to -20% VoutOutput Current10ARipple and noise50mV pk-pkRegulationLoad regulation =10mV, Line regulation = 5mVSwitching FrequencyFixed switching frequency 165KhzIsolation Voltage2000Vdc100mV deviation 150uS recovery	Output specification	
(25%-50% ~ 25% lout)	Trim range Output Current Ripple and noise Regulation Switching Frequency	+10% to -20% Vout 10A 50mV pk-pk Load regulation =10mV, Line regulation = 5mV Fixed switching frequency 165Khz 2000Vdc 100mV deviation 150uS recovery

Environmental Specification

Storage Temperature-55 to +125 deg CAmbient operating temp-40 to +85 deg CMTBF at 25degC1.5 Million hoursOTP118 deg C



DC/DC Product Specification

Embedded Power for **Business-Critical Continuity**

1/8th brick fully regulated DCDC converter.

Mechanical







Unit: mm[inch] Bottom view: pin on upside Tolerance: X.Xmm \pm 0.5mm[X.X in. \pm 0.02in.] X.XXmm ±0.25mm[X.XX in. ±0.01in.]

Ordering information

Input voltage	Output voltage	Output current	Efficiency	Part number
48V	12V	10A	93%	AVO120-48S12-6L
48V	12V	10A	93%	AVO120-48S12B-6L
48V	12V	10A	93%	AVO120-48S12P-6L
48V	12V	10A	93%	AVO120-48S12PB-6L
48V	12V	10A	93%	AVO120-48S12-4LE

Notes

- Standard converter is Negative enable
- -6' = 3.8mm pin length.
- '-P' = Positive remote control,
- '-L' = RoHS-6 compliant.
- '-B' = Base-plate

Notes.

- 1\20Mhz bandwidth. External 10uF tantalum capacitor placed across +Vout and -Vout; 33 uF e-cap or equivalent placed across +Vin and -Vin.
- 2\ Efficiency measurements taken at full load and nominal line and Tamb = 25degC
- 3\ All specifications taken at nominal line, full load and Tamb = 25degC unless otherwise noted
- 4\ Mechanical dimensions are for reference only. Dimensions are in MM. Mechanical tolerance = +/-0.5mmm
- 5\ Technical reference notes should be consulted for detailed information when available.
- 6\ All specifications subject to change without notice

7\ Warranty 2 years

8\ The through-hole terminated modules are intended for wave-soldering process - special request for other manufacturing processes to be made to Emerson

Rev 09/07/2012 AVO120 series
Page 2 of 2

Americas

Pin Assignments

Function

+V in

Enable

-V in

- Sense

Trim

+Sense

+V out

-V out

Pin #

1

2

3

4

5

6

7

8

5810 Van Allen Way Carlsbad, CA 92008 USA Telephone: +1 (760) 930 4600 Facsimile: +1 (760) 930 0698

Europe (UK)

Waterfront Business Park Merry Hill, Dudley West Midlands, DY5 1LX United Kingdom Telephone: +44 (0) 1384 842 211 Facsimile: +44 (0) 1384 843 355

Asia (HK)

14/F, Lu Plaza 2 Wing Yip Street Kwun Tong, Kowloon Hong Kong Telephone: +852 2176 3333 Facsimile: +852 2176 3888

For global contact, visit:

www.powerconversion.com

techsupport.embeddedpower @emerson.com

While every precaution has been taken to ensure accuracy and completeness in this literature. Emerson Network Power assumes no responsibility, and disclaims all liability for damages resulting from use of this information or for any errors or omissions.

Emerson Network Power.

The global leader in enabling business-critical continuity.



EmersonNetworkPower.com

Emerson Network Power and the Emerson Network Power logo are trademarks and service marks of Emerson Electric Co. ©2008 Emerson Electric Co.

