ON Semiconductor

Is Now

Onsemi

To learn more about onsemi[™], please visit our website at <u>www.onsemi.com</u>

onsemi and ONSEMI. and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product factures, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using onsemi products, including compliance with all laws, regulations and asfety requirements or standards, regardless of any support or applications information provided by onsemi. "Typical" parameters which may be provided in onsemi data sheets and/or by customer's technical experts. onsemi products and actal performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. onsemi products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use onsemi products for any such unintended or unauthorized application, Buyer shall indemnify and hold onsemi and its officers, employees, subsidiari



ON Semiconductor® BS270 N-Channel Enhancement Mode Field Effect Transistor

General Description

These N-Channel enhancement mode field effect transistors are produced using ON Semiconductor's proprietary, high cell density, DMOS technology. These products have been designed to minimize on-state resistance while provide rugged, reliable, and fast switching performance. They can be used in most applications requiring up to 500mA DC. These products are particularly suited for low voltage, low current applications such as small servo motor control, power MOSFET gate drivers, and other switching applications.

Features

- 400mA, 60V. $R_{DS(ON)} = 2\Omega @ V_{GS} = 10V.$
- High density cell design for low R_{DS(ON)}.
- Voltage controlled small signal switch.
- Rugged and reliable.
- High saturation current capability.



Absolute Maximum Ratings $T_A = 25^{\circ}C$ unless otherwise noted

Symbol	Parameter	BS270	Units
V _{DSS}	Drain-Source Voltage	60	V
V _{dgr}	Drain-Gate Voltage ($R_{gs} \le 1M\Omega$)	60	V
V _{GSS}	Gate-Source Voltage - Continuous	±20	V
	- Non Repetitive (tp < 50µs)	±40	
I _D	Drain Current - Continuous	400	mA
	- Pulsed	2000	
P _D	Maximum Power Dissipation	625	mW
	Derate Above 25°C	5	mW/°C
Γ _J ,T _{stg}	Operating and Storage Temperature Range	-55 to 150	°C
T _L	Maximum Lead Temperature for Soldering Purposes, 1/16" from Case for 10 Seconds	300	°C
THERMA	L CHARACTERISTICS		·
R _{eja}	Thermal Resistacne, Junction-to-Ambient	200	°C/W

Symbol	Parameter	Conditions		Min	Тур	Max	Units
OFF CHAP	RACTERISTICS						
BV _{DSS}	Drain-Source Breakdown Voltage	$V_{gg} = 0 V, I_{p} = 10 \mu A$		60			V
I _{DSS}	Zero Gate Voltage Drain Current	$V_{DS} = 60 \text{ V}, V_{GS} = 0 \text{ V}$				1	μA
			T _J = 125°C			500	μA
	Gate - Body Leakage, Forward	$V_{gg} = 20 V, V_{Dg} = 0 V$	·			10	nA
	Gate - Body Leakage, Reverse	$V_{gg} = -20 \text{ V}, V_{dg} = 0 \text{ V}$				-10	nA
ON CHAR	ACTERISTICS (Note 1)						
V _{GS(th)}	Gate Threshold Voltage	$V_{\rm DS} = V_{\rm GS}, I_{\rm D} = 250 \; \mu \text{A}$		1	2.1	2.5	V
R _{DS(ON)}	Static Drain-Source On-Resistance	V _{gs} = 10 V, I _p = 500 mA			1.2	2	Ω
			T _J = 125°C		2	3.5	
		V _{gs} = 4.5 V, I _p = 75 mA			1.8	3	
V _{DS(ON)}	Drain-Source On-Voltage	$V_{GS} = 10 \text{ V}, \ \text{I}_{D} = 500 \text{ mA}$			0.6	1	V
		$V_{GS} = 4.5 \text{ V}, I_{D} = 75 \text{ mA}$			0.14	0.225	
I _{D(ON)}	On-State Drain Current	$V_{GS} = 10 \text{ V}, V_{DS} \ge 2 \text{ V}_{DS(on)}$		2000	2700		mA
		$V_{\text{GS}} = 4.5 \text{ V}, \ V_{\text{DS}} \geq 2 \text{ V}_{\text{DS(on)}}$		400	600		
g _{FS}	Forward Transconductance	$V_{\text{DS}} \ge 2 V_{\text{DS(on)}}, I_{\text{D}} = 200 \text{ mA}$		100	320		mS
DYNAMIC	CHARACTERISTICS						-
C _{iss}	Input Capacitance	$V_{DS} = 25 V, V_{GS} = 0 V,$ f = 1.0 MHz			20	50	pF
C _{oss}	Output Capacitance	f = 1.0 MHz			11	25	pF
C _{rss}	Reverse Transfer Capacitance				4	5	pF
SWITCHIN	G CHARACTERISTICS (Note 1)						
t _{on}	Turn-On Time	$V_{DD} = 30 \text{ V}, \ \text{I}_{D} = 500 \text{ m A},$				10	ns
t _{off}	Turn-Off Time	V_{GS} = 10 V, R_{GEN} = 25 Ω				10	ns
DRAIN-SO	URCE DIODE CHARACTERISTICS AND	MAXIMUM RATINGS					-
s	Maximum Continuous Drain-Source Diode Forward Current				400	mA	
I _{SM}	Maximum Pulsed Drain-Source Diode Forward Current				2000	mA	
V _{SD}	Drain-Source Diode Forward Voltage	$V_{GS} = 0 \text{ V}, \text{ I}_{S} = 400 \text{ mA} (\text{Note 1})$			0.88	1.2	V



www.onsemi.com 3







6 www.onsenn.c







www.onsemi.com

ON Semiconductor and are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at <u>www.onsemi.com/site/pdf/Patent-Marking.pdf</u>. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor haves, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such uninten

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910

Japan Customer Focus Center Phone: 81–3–5817–1050 ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative