**Technical Data Sheet** 

COAXIAL TERMINATION N MALE 2 GHZ 6W



Radiall 💓

This document contains proprietary information and such information shall not be disclosed to any third party for any purpose whatsoever or used for manufacturing purposes without prior written agreement from Radiall. The data defined in this document are given as an indication, in the effort to improve our products; we reserve the right to make any changes judged necessary.



COAXIAL TERMINATION N MALE 2 GHZ 6W



	2/2 ISSUE 27-04-		SERIE CHAR	PART NUMBER <b>R404507000</b>			
			I	ELECTRICAL C	HARACTERISTICS		
Γ	Frequency (	GHz)	DC - 2				
	V.S.W.R (≤)		1.10				
C	perating Fre	quency Ra	ange	DC - 2			Hz
	Impedance DC Resistance Peak power at 25°C (1µs, 1%o) Average power at 25°C			50 50 4000 6		Ω	
							Ω ± 5%
						V.	/ / (Free Air Cooled)
-							(Conduction Cooled)
							· · · · · · · · · · · · · · · · · · ·
			<u>1</u>		HARACTERISTICS		
0	connectors		N		Male		MIL C 39012
	Veight	4	<b>15,9800</b> g			1	
			Dover (%) Power (%)	-55 .15	25 75 125 mperature (°C)		
				SPECI	FICATION		

This document contains proprietary information and such information shall not be disclosed to any third party for any purpose whatsoever or used for manufacturing purposes without prior written agreement from Radiall. The data defined in this document are given as an indication, in the effort to improve our products; we reserve the right to make any changes judged necessary.