1550 Standard and 1350 High Inrush

 \bigcirc

 \bigcirc

150A to EN61058-1 and 16A 250Vac





Key Features

- Standard rocker switch 🗘 Matching indicator
 - O Double Contact
 - O Splash resistant option
 - Panel cut out 'A' style:
 27.2 x 22.3mm
- Push-on, solder and PCB terminals

1350/53 high inrush

Choice of switching

circuits including 3

position

- Choice of bezel styles
- Choice of panel cut outs

Approvals and specifications

- Mr 1550 Series 16(4)A 250Vac T125
- UL CSA 16A 250Vac, (2 posn) 250Vac 1hp, 125Vac 1/2hp, 1350 72 Vdc 7A
 (3 posn) 250 Vac 1/2hp, 125Vac 1/4hp.
 UL 85°C, file E45221, CSA file LR10990.

In house test: 10A 24Vdc—Indicative rating only. NB Types fitted with Neon will not illuminate for low DC voltage applications.

1350 series 16(4)A 250Vac T85 1E4 (10,000 Ops.)
 1330 series 16(6)A 250Vac T125 5E4 (50,000 Ops.)
 150A Inrush to EN61058-1.





Approvals and specifications (continued)

SN € UL CSA 20A 250Vac 1hp, 125Vac 1/2hp. UL 72Vdc 7A, 36Vdc 14A. UL 85°C, file E45221, CSA file LR10990.

> In house test: 20A 24Vdc—Indicative rating only

3mm contact gap except if marked μ .

Splash Resistance



1300 High inrush, positive break switching The 1300 series mechanism ensures contact welds formed at switch-on are positively separated by the plunger tube acting directly on the step in the moving contact.

Dimensions

0-+1	25,31	ABX 🙀	
• '	-7.6		
			13 9.3

Panel thickness A,Q 0.75 to 3.3mm L,B,T 0.75 to 2.5mm R 0.75 to 3.0mm

* For cut-out details on momentary switches call sales



1550 Standard & 1350 High Inrush Switches 150A to EN61058-1 and 16A 250Vac250Vac





Key Features

1350/53 high inrush

position

Choice of switching

circuits including 3

Push-on, solder and PCB terminals

 \bigcirc

- Standard rocker switch O Matching indicator
 - O Double Contact
 - Option with guard & cover
 - O DC LED Illumination Available for "P" Rocker
 - O Bezel size 'G' style 32.0 x 25.0
- Choice of bezel styles ○ Choice of panel cut outs

Approvals and specifications

- « 1550 Series 16(4)A 250Vac T125
- **N** UL CSA 16A 250Vac, (2 posn) 250Vac 1hp, 125Vac 1/2hp, (3 posn) 250 Vac 1/2hp, 125Vac 1/4hp. UL 85°C, file E45221, CSA file LR10990.

In house test: 10A 24Vdc-Indicative rating only

1350 Series

№ UL CSA 20A 250Vac 1hp, 125Vac 1/2hp. UL 72Vdc 7A, 36Vdc 14A, UL 85°C, file E45221, CSA file LR10990.

Terminal	Funct	ion	Rocker	Body	Finish	Body Colour	Rocker Colour	
C	Standard 1550	ON - OFF	A Softline Matt	Panel cut-out Bezel Cut-outs must be punched in the direction of insertion	M Matt	B Black	Un-Lit B Black	
6.3 × 0.8	1551 HP rating N/A	ON - OFF (momentary ON)			•		R Red	
H	1552 HP rating N/A	ON - OFF (momentary OFF)		Matt only	G Gloss	White	W White	
4.8 × 0.8*	1553 Not W, X or B rocker	ON - OFF Lit	V Curved		Applies to both Rocker & Body		Lit	
K	1560 µ	ON - ON	Matt or Gloss Gloss only Lit (not momentary)	<u>i</u> 22.1/22.2 i <u>25.0</u> i <u>i</u> Matt only			Amber G	
	1561 μ ^{HP} rating N/A	ON - ON (Momentary 1 Side)					Green	
2.8 x 0.8*	1562 µ In house tests only	ON - ON 2 Circuit					Clear R Red	
T _{∞2.1} <u>1</u> 7.0	1570 µ 125V & 250V 1/2 HP H terminal rated T100 onlyH terminal rated T100 only	ON - OFF - ON	P Lit window Matt					
Solder	1571 μ HP rating N/A H terminal rated T100 only	ON - OFF - ON (momentary 1 side)	Lit (not momentary)					
0 02.1 ↓ 02.1 ↓	1572 μ HP rating N/A H terminal rated T100 only	ON - OFF - ON (momentary 2 sides)						
Right angle T Solder (Not DP)	High Inrush 1350 Not W, X or B rocker	ON - OFF						
	1353 Not W, X or B rocker	ON - OFF Lit						
PCB 0.8Sq* *Contact sales for details on 1350 series		Lit						
362 Switches								



In house test: 20A 24Vdc—Indicative rating only

3mm contact gap except if marked μ .

Splash Resistance



1350 High inrush, positive break switching The 1350 series mechanism ensures contact welds formed at switch-on are positively separated by the plunger tube acting directly on the step in the moving contact.

Dimensions



 Panel thickness

 G, H
 0.75 to 2.5mm

 Terminal spacing - Contacts 10.2 between centres

 * For cut-out details on momentary switches call sales



Examples





C1553AH - - -

⊡ C1550AH - - -