

Monolithic Amplifier

AVA-24A+

Mini-Circuits

50Ω 5 to 20 GHz

THE BIG DEAL

- Surface Mount Amplifier up to 20 GHz
- Integrated matching, DC Blocks and bias circuits
- High Reverse Isolation
- Gain, 12.3 dB typ. & Flatness, ±1.3 dB
- Output Power, up to +18.3 dBm typ.
- Excellent isolation, 36 dB typ.
- Single Positive Supply Voltage, +5V
- Integrated DC blocks, Bias-Tee & Microwave bypass capacitor
- Unconditionally Stable
- Aqueous washable; 3mm x 3mm SMT package



Generic photo used for illustration purposes only

CASE STYLE: DQ849

+RoHS Compliant The +Suffix identifies RoHS Compliance. See our website for methodologies and qualifications

APPLICATIONS

- Military EW and Radar
- DBS
- Wideband Isolation amplifier
- Microwave point-to-point radios
- Satellite systems

PRODUCT OVERVIEW

The Mini-Circuits AVA-24A+ is a surface mount, microwave amplifier fabricated using InGaAs PHEMT technology and is fully integrated gain block up to 20 GHz. It is packaged in Mini-Circuits industry standard 3x3 mm MCLP (QFN) package, which provides excellent RF and thermal performance. The AVA-24A+ integrates the entire matching network with the majority of the bias circuit inside the package, reducing the need for complicated external circuits. This approach makes the AVA-24A+ extremely flexible and enables simple, straightforward use.

KEY FEATURES

Feature	Advantages
Wideband, 5 to 20 GHz	Broad frequency range supports a wide array of applications from microwave radio and radar , to military communications and countermeasures.
Excellent Gain Flatness	Typical ±0.8 dB gain flatness across the entire frequency range minimizes the need for external equalizer networks making it a great fit for instrumentation and EW applications.
High Isolation	With reverse isolation of 36 dB (24 dB directivity), the AVA-24A+ is an excellent choice for buffering broadband circuits. It is an ideal LO driver amplifier and provides designers system flexibility and margin when integrating cascaded RF components.
Manufacturability	MSL1 and ESD Class1A (HBM) ratings minimize special handling on production lines.



Monolithic Amplifier



ELECTRICAL SPECIFICATIONS⁽¹⁾ AT 25°C, Zo=50Ω, (REFER TO CHARACTERIZATION CIRCUIT, FIG. 1)

Parameter	Condition (GHz)	Min.	Тур.	Max.	Units
Frequency Range		5.0		20.0	GHz
DC Voltage (V _{D1} , V _{D2})			5.0		V
DC Current (I _{D1} +I _{D2})			120	147	mA
	5.0	_	12.2		
	8.0	10.0	12.8		
	10.0	10.0	12.4		dB
	12.0	_	11.8		
Gain	14.0	_	11.5		
	16.0	_	11.6		
	18.0	_	11.3		
	20.0	8.5	10.1		
	5.0	_	12.2		
	8.0	10.0	14.5		
	10.0	10.0	19.3		dB
	12.0	_	15.9		
nput Return Loss	14.0	_	15.7		
	16.0	10.0	13.8		
	18.0	_	9.2		
	20.0	_	7.0		
	5.0		9.2		dB
	8.0		10.6		
	10.0		13.1		
	12.0		11.6		
Dutput Return Loss	14.0		11.8		
	16.0		11.3		
	18.0		11.3		
	20.0		11.4		
	5.0		27.2		
	8.0		26.6		
	10.0		25.7		
	12.0		25.0		
Output IP3	14.0		24.0		dBm
	16.0		22.9		
	18.0		22.0		
	20.0		21.4		
	5.0	_	18.1		+
	8.0	_	19.1		
	10.0	16.0	18.9		
	12.0	_	18.4		dBm
Output Power @ 1 dB compression	14.0	_	18.7		
	16.0	_	19.4		
	18.0	_	20.0		
	20.0	_	18.6		
	5.0		9.0		dB
	8.0		5.1		
	10.0		5.3		
	12.0		5.7		
Noise Figure	14.0		6.0		
	16.0		6.3		
	18.0		6.7		
	20.0		6.9		
Directivity (Isolation-Gain)			24.0		dB
DC Current Variation vs. Temperature ⁽²⁾			0.050		mA/°C
OC Current Variation vs. Voltage			0.002		mA/mA
Thermal Resistance			53		°C/W



Monolithic Amplifier



Mini-Circuits

MAXIMUM RATINGS⁽³⁾

Parameter	Ratings
Operating Temperature (4)	-40°C to 85°C
Storage Temperature	-55°C to 100°C
Channel Temperature	150°C
DC Voltage (Pad 7,8)	+5.5V
Voltage (Pads 2, 5)	+10V
Power Dissipation	860 mW
DC Current (Pad 7+8) at V _D =5V	160mA
Input Power	+20 dBm

(1) Measured on Mini-Circuits Characterization test fixture TB-547-1A+. See Characterization Test Circuit (Fig. 1) (2) (Current at 85°C - Current at -45°C)/130

(3) Permanent damage may occur if any of these limits are exceeded. These maximum ratings are not intended for continuous normal operation.
(4) Defined with reference to ground pad temperature.

SIMPLIFIED SCHEMATIC AND PAD DESCRIPTION





Pad Number	Description (See Application Circuit, Fig. 2)
2	RF input pad
5	RF output pad
8(V _{D1}), 7 (V _{D2})	DC power supply
paddle in center of bottom	Connected to ground
1,3,4,6	No internal connection; recommended use: per PCB Layout PL-328
	2 5 8(V _{D1}), 7 (V _{D2}) paddle in center of bottom

*Pseudomorphic High Electron Mobility Transistor.



Monolithic Amplifier



Mini-Circuits

CHARACTERIZATION TEST CIRCUIT



C1=5.6pF, 0402 (NPO) C2=18pF, 0402 (NPO) C3=0.001µF, 0402 (NPO) C4=0.1 µF, 0402 (X7R) L1=3.3nH, 0805 (wire wound)

Refer to 98-PL-328

Fig 1. Block Diagram of Test Circuit used for characterization. (DUT soldered on Mini-Circuits Characterization Test Board TB-547-1A+) Gain, Output power at 1dB compression (P1dB), Noise Figure, Output IP3 (OIP3) are measured using Agilent's N5242A PNA-X microwave network analyzer.

Conditions:

1. Gain: Pin=-25 dBm

2. Output IP3 (OIP3): Two tones, spaced 1 MHz apart, +8 dBm/tone at output.

3. Vs adjusted for 5V at device (VD1 and VD2), compensating loss of bias lines.

RECOMMENDED APPLICATION CIRCUIT

(refer to evaluation board for PCB Layout and component values)



Fig 2. Recommended Application Circuit

PRODUCT MARKING



black body

model family designation

Marking may contain other features or characters for internal lot control



Monolithic Amplifier

Mini-Circuits

ADDITIONAL DETAILED TECHNICAL INFORMATION IS AVAILABLE ON OUR DASH BOARD. TO ACCESS CLICK HERE

Performance Data	Data Table Swept Graphs S-Parameter (S2P Files) Data Set (.zip file)
Case Style	DQ849 Plastic package, exposed paddle, lead finish: tin silver nickel
Tape & Reel Standard quantities available on reel	F104 7" reels with 10, 20, 50, 100, 200, 500,1K, 2K
Suggested Layout for PCB Design	PL-328
Evaluation Board	TB-547-1A+
Environmental Ratings	ENV08T1

ESD RATING

Human Body Model (HBM): 1A (250 to <500V) in accordance with ANSI/ESD STM 5.1 - 2001

Machine Model (MM): M1 (Pass 50V) in accordance with ANSI/ESD STM5.2-1999; passes 25V

MSL RATING

Moisture Sensitivity: MSL1 in accordance with IPC/JEDEC J-STD-020D

MSL TEST FLOW CHART



NOTES

- A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.
- B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.
- C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the standard. Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp

Mini-Circuits