# **QR/P1 SERIES CONNECTOR**

Small Rectangular Multi-electrode Solderless Connectors for Racks and Panels

#### General

QR/P series connectors are small and compact high density versions of original OR/P series. Available in 8,

12, 16, 24 and 32 way. Crimps terminals assure positive and reliable termination with minimum labor.



#### Features

- The coupling mechanism assures stable and reliable contact pressure through point and blade contact, in addition to smooth coupling that is sufficiently capable of dealing with variations in the coupling length specific to the plug-in connection.
- 2. Compact contacts due to separate power contacts from signal contacts.
- One opposed pair (in 12 contacts), 2 pairs (in 8, 16, and 24 contacts), and 3 pairs (in 32 contacts) can be used as power supply contacts. They are spaced

further apart that the others so as to have enough creeping distance to withstand a high voltage. Fire-retardant insulation materials (UL94-0) are used.

- 4. The Guide Pin is made of steel nickel plated to be strong enough against accidental coupling shock.
- The mount of a receptacle housing is done through Floating Bushes. Thus, they may help to give more smooth coupling of connectors by self-adjusting function.

#### Application

PPC, Transmission and reception equipment, Data Communication, Vending Machine, Measuring Instruments, Automatic Equipment, Switchboards, etc.

## How To Use Connectors

G	General rating of QR/P1			Material						
	Power unit	10m $\Omega$ or less at DC1A	Insulator Polyethy		Polyethy	lene terephtalate		Black		
Contact resistance	Signal unit	10m $\Omega$ or less at DC1A	Termi	nal	Phos	phor bronz	æ	Selective g with nickel		
Insulation resistance	5000M $\Omega$ higher at DV 500V							with mckei		1g
Withstand voltage	Power terminal	AC 1000V						/P1 safety s		militar
(for 1 min.)	Signal terminal	AC 500V	Safety standard		U	L	CS	SA	TÜV	
	Power unit	13Amax (AWG #14 use)	Operating temperature range				- 10~ +	℃00		
Rated current	Signal unit	3A			Power					AC250, DC300V
Rated voltage	Power terminal	AC 250V	Rated vo	oltage	supply	- AC120V	AC250V	AC125V	AC250V	
Kated voltage	Signal terminal AC 125V Signal unit					AC125, DC150V				
				AV	WG#14	10.1		10A	10A 2.4	10A
			A		WG#16	- 10A	3A	8A	- 3A	IUA
				A	WG#18					5A
			Rated current	A	WG#20	3A	1A	3A	1A	2.5A
				A١	WG#22					
				current	AWG	Power supply	2A	1A	2A	1A
				#24	Signal unit	1A	0.5A	1A	0.5A	IA
					WG#26 WG#28	1A	0.5A	1A	0.5A	

## **Ordering Information**

▲ Connector unit	$\frac{\mathbf{QR} / \mathbf{P1}}{\begin{vmatrix} \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\ \\$
▲ Terminal	$\frac{QR / P1}{(1)} - \frac{PC 1 A}{(5)(6)(7)} - \frac{1}{(8)(9)(10)}$
(1) Series name	(7) Crimp barrel size
(2) No.of contacts (8, 12, 16, 24	, 32) A: For thin wires
(3) Shape of insulator mating p	art B: For thick wires
P: Insulator male case	(8) Shape
S: Insulator female case	1: Loose piece terminal
(4) Type of termination	2: Strip terminal
C: Crimp terminal	(9) Applicable wire
(5) Male/ Female	1: Power terminal AWG # 18 - # 24
PC: Male crimp terminal	Signal terminal AWG # 24 - # 28
SC: Female crimp terminal	2: Power terminal AWG # 14 - # 16
(6) Type	Signal terminal AWG # 20 - # 24
1: Power terminal	(10) Surface terminal
2: Signal terminal	1: Selective gold plating with nickel underplating
	(11) Specifications meeting UL, CSA TÜV requirements

### Contacts for thick wire Contact Configuration

Male Housing (Viewed from Wiring Side)

: indicates a contact hole for thick wire



QR/P1-8P-C (51)



QR/P1-12P-C (51)



QR/P1-16P-C (51)

1	2	3	4	5	6	7	8	9	10	11	12
22	Π										
64928		1000		-	-	-				_	1000
	п	$\square$							22		22
6223		<u> </u>		<u> </u>				5	5	57	200

QR/P1-24P-C (51)



QR/P1-32P-C (51)

# Housing



Note: Determine the combinations with the panel so that the mating clearance between the P side and S side is 1.5mm or less.

# **Crimp Contact (Power Circuit)**



Plating: Partly gold plated over nickel plating

Applicable Wire	HRS No.	Part No.	Туре	Packing	RoHS	Applicable Wire
AWG#14~16	CL221-0114-7-12	QR/P1-PC1B-121 (12)	Loose contact	100pin		AWG#14~1
AWG#14~10	CL221-0118-8-12	QR/P1-PC1B-221 (12)	Chain contact	3,000pin		AWG#14.01
AWG#18~24	CL221-0102-8-12	QR/P1-PC1A-111(12)	Loose contact	100pin		AWG#18~24
AWG#18~24	CL221-0106-9-12	QR/P1-PC1A-211(12)	Chain contact	5,000pin		AWG#10 - 24



Plating: Partly gold plated over nickel plating

Applicable Wire	HRS No.	Part No.	Туре	Packing	RoHS
AWG#14~16	CL221-0116-2-12	QR/P1-SC1B-121(12)	Loose contact	100pin	
AWG#14~16	CL221-0120-0-12	QR/P1-SC1B-122(12)	Chain contact	3,000pin	$\cap$
AWG#18~24	CL221-0104-3-12	QR/P1-SC1A-111 (12)	Loose contact	100pin	0
A W 6#10 <sup>-24</sup>	CL221-0108-4-12	QR/P1-SC1A-211 (12)	Chain contact	5,000pin	

# **Crimp Contact (Signal Circuit)**



	Plated: Gold	plated over nickel	plating		
Applicable Wire	HRS No.	Part No.	Туре	Packing	RoHS
AWG#20 ~ 24	CL221-0115-0-12	QR/P1-PC2B-121 (12)	Loose contact	100pin	
A WG#20 - 24	CL221-0119-0-12	QR/P1-PC2B-221 (12)	Chain contact	3,000pin	0
AWG#24 ~ 28	CL221-0103-0-12	QR/P1-PC2A-111(12)	Loose contact	100pin	0
AWG#24 - 20	CL221-0107-1-12	QR/P1-PC2A-211(12)	Chain contact	5,000pin	



	Plated: Gold	plated over nickel	plating		
Applicable Wire	HRS No.	Part No.	Туре	Packing	RoHS
AWG#20 ~ 24	CL221-0117-5-12	QR/P1-SC2B-121(12)	Loose contact	100pin	
A W G#20 ~ 24	CL221-0121-2-12	QR/P1-SC2B-122(12)	Chain contact	3,000pin	0
AWG#24 $\sim$ 28	CL221-0105-6-12	QR/P1-SC2A-111 (12)	Loose contact	100pin	0
л w G#24 ~ 28		QR/P1-SC2A-211 (12)	Chain contact	5,000pin	

# **Recommended Mounting Hole**



No. of p	No. of pin		12 Pin	16 Pin	24 Pin	32 Pin
	A	36.9	42	48.1	59.3	76
Rear	В	29.4	34.5	40.6	51.8	68.5
Mount- ing	С	28.4	33.5	39.6	50.8	67.5
	D	4.3	3.3	4.3	4.3	4.3
Front Mount- ing	Е	22.4	27.5	33.6	44.8	61
	F	36.9	42	48.1	59.3	76
	G	4.3	3.3	4.3	4.3	4.3

# **Applicable Tools**

