



DUAL N-CHANNEL ENHANCEMENT MODE MOSFET

Product Summary

BVDSS	Rds(on) Max	I _D Max T _A = +25°C
30V	16mΩ @ V _{GS} = 10V	9.8A
300	22mΩ @ V _{GS} = 4.5V	8.4A

Description

This MOSFET has been designed to minimize the on-state resistance (RDS(ON)) yet maintain superior switching performance, making it ideal for high efficiency power management applications.

Applications

- Backlighting
- Power management functions
- DC-DC converters

Features and Benefits

- 100% Avalanche Rated Part
- Low RDS(ON) Minimizes Conduction Losses
- Low Q_q Minimizes Switching Losses
- Totally Lead-Free & Fully RoHS Compliant (Notes 1 & 2)
- Halogen and Antimony Free. "Green" Device (Note 3)
- For automotive applications requiring specific change control (i.e.: parts qualified to AEC-Q100/101/104/200, PPAP capable, and manufactured in IATF 16949 certified facilities), please refer to the related automotive grade (Q-suffix) part. A listing can be found at

https://www.diodes.com/products/automotive/automotive-products/.

 This part is qualified to JEDEC standards (as references in AEC-Q) for High Reliability.


https://www.diodes.com/quality/product-definitions/

Mechanical Data


- Package: SO-8
- Package Material: Molded Plastic, "Green" Molding Compound.
 UL Flammability Classification Rating 94V-0
- Moisture Sensitivity: Level 1 per J-STD-020
- Terminal Connections Indicator: See Diagram
- Terminals: Finish Matte Tin Annealed over Copper Leadframe. Solderable per MIL-STD-202, Method 208 (3)
- Weight: 0.076 grams (Approximate)




Top View



Pin Configuration Internal Schematic



N-Channel MOSFET



N-Channel MOSFET

Ordering Information (Note 4)


Part Number	Package	Packing		
	Fackage	Qty.	Carrier	
DMG4800LSD-13	SO-8	2,500	Tape & Reel	

Notes:

- 1. No purposely added lead. Fully EU Directive 2002/95/EC (RoHS), 2011/65/EU (RoHS 2) & 2015/863/EU (RoHS 3) compliant.
- 2. See https://www.diodes.com/quality/lead-free/ for more information about Diodes Incorporated's definitions of Halogen- and Antimony-free, "Green" and Lead-free.
- 3. Halogen- and Antimony-free "Green" products are defined as those which contain <900ppm bromine, <900ppm chlorine (<1500ppm total Br + Cl) and <1000ppm antimony compounds.
- 4. For packaging details, go to our website at https://www.diodes.com/design/support/packaging/diodes-packaging/.



Marking Information



⊃¦¦= Manufacturer's Marking G4800LD = Product Type Marking Code YYWW = Date Code Marking YY or YY = Year (ex: 22 = 2022) WW = Week (01 to 53)

YY = Date Code Marking for SAT (Shanghai Assembly/Test Site) YY = Date Code Marking for CAT (Chengdu Assembly/Test Site)

Maximum Ratings (@T_A = +25°C, unless otherwise specified.)

Characteristic			Symbol	Value	Units
Drain-Source Voltage			V _{DSS}	30	V
Gate-Source Voltage			V _{GSS}	±25	V
Continuous Durin Compart (Note 5) // 40)/	Steady State	T _A = +25°C T _A = +70°C	I _D	7.5 6.0	А
Continuous Drain Current (Note 5) V _{GS} = 10V	t < 10s	T _A = +25°C T _A = +70°C	lD	9.8 7.7	А
Continuous Drain Current (Note 5) Vos. 45V	Steady State	$T_A = +25$ °C $T_A = +70$ °C	lo	6.4 5.0	Α
Continuous Drain Current (Note 5) Vgs = 4.5V	t < 10s	$T_A = +25$ °C $T_A = +70$ °C	lo	8.4 6.6	Α
Maximum Continuous Body Diode Forward Current (Note 5)			Is	2	Α
Pulsed Drain Current (10µs Pulse, Duty Cycle = 1%)			I _{DM}	42	А
Avalanche Current (Notes 6 & 7) L = 0.1mH			lar	17	А
Repetitive Avalanche Energy (Notes 6 & 7) L = 0.1mH			Ear	14	mJ

Thermal Characteristics

Characteristic	Symbol	Value	Units		
Total Power Dissipation (Note 8)		PD	1.17	W	
Thermal Desistance Investigate Ambient (Nets 8)			107	°C/W	
Thermal Resistance, Junction to Ambient (Note 8)	t < 10s	$R_{\theta JA}$	61	C/VV	
Total Power Dissipation (Note 5)		PD	1.5	W	
The arrest Begintenes, Juneties to Ambient (Note 5) Steady State		D	83		
Thermal Resistance, Junction to Ambient (Note 5)	t < 10s	Reja	49	°C/W	
Thermal Resistance, Junction to Case		Rejc	14.5		
Operating and Storage Temperature Range		TJ, TSTG	-55 to +150	°C	

Notes:

- 5. Device mounted on FR-4 substrate PC board, 2oz copper, with 1inch square copper plate.
- 6. I_{AR} and E_{AR} ratings are based on low frequency and duty cycles to keep T_{J} = +25°C.
- Applicable to products manufactured with Data Code "1146" (Nov, 2011) and newer.
 Device mounted on FR-4 substrate PC board, 2oz copper, with minimum recommended pad layout.




Electrical Characteristics (@T_A = +25°C, unless otherwise specified.)

Characteristic	Symbol	Min	Тур	Max	Unit	Test Condition	
OFF CHARACTERISTICS (Note 9)							
Drain-Source Breakdown Voltage	BVDSS	30		_	V	$V_{GS} = 0V, I_{D} = 250\mu A$	
Zero Gate Voltage Drain Current T _J = +25°C	I _{DSS}	_	_	1.0	μA	$V_{DS} = 30V$, $V_{GS} = 0V$	
Gate-Source Leakage	Igss	_	_	±100	nA	$V_{GS} = \pm 20V$, $V_{DS} = 0V$	
ON CHARACTERISTICS (Note 9)							
Gate Threshold Voltage	Vgs(TH)	0.8	_	1.6	V	$V_{DS} = V_{GS}$, $I_D = 250\mu A$	
Static Drain-Source On-Resistance	Descent		12	16 22	mΩ	$V_{GS} = 10V, I_D = 9A$	
Static Dialit-Source Off-Resistance	RDS(ON)	_	16		11122	$V_{GS} = 4.5V, I_D = 7A$	
Forward Transfer Admittance	Y _{fs}	_	8	_	S	$V_{DS} = 10V, I_{D} = 9A$	
Diode Forward Voltage	VsD	_	0.72	0.94	V	$V_{GS} = 0V$, $I_{S} = 1A$	
DYNAMIC CHARACTERISTICS (Note 10)							
Input Capacitance	C _{iss}	_	798	_	pF	101/1/	
Output Capacitance	Coss	_	128	_	pF	V _{DS} = 10V, V _{GS} = 0V f = 1.0MHz	
Reverse Transfer Capacitance	Crss	_	122	_	pF		
Gate Resistance	Rg	_	1.37	_	Ω	$V_{DS} = 0V$, $V_{GS} = 0V$, $f = 1MHz$	
Total Gate Charge	Qg	_	8.56	_	nC	V _G S = 5V, V _D S = 15V I _D = 9A	
Gate-Source Charge	Qgs	_	1.8	_	nC		
Gate-Drain Charge	Q_{gd}	_	2.5	_	nC		
Turn-On Delay Time	td(ON)	_	5.03	_	ns	$V_{DD}=15V,\ V_{GEN}=10V$ $R_{L}=15\Omega,\ R_{G}=6\Omega,\ I_{D}=1A$	
Turn-On Rise Time	t _R	_	4.50	_	ns		
Turn-Off Delay Time	tD(OFF)	_	26.33	_	ns		
Turn-Off Fall Time	t _F	_	8.55	_	ns		

Notes:

^{9.} Short duration pulse test used to minimize self-heating effect. 10. Guaranteed by design. Not subject to product testing.











Fig. 7 Gate Threshold Variation vs. Ambient Temperature








Fig. 11 Typical Leakage Current vs. Drain-Source Voltage












Fig. 12 Transient Thermal Response




Package Outline Dimensions

Please see http://www.diodes.com/package-outlines.html for the latest version.








SO-8

	SO-8					
Dim	Min	Max	Тур			
Α	1.40	1.50	1.45			
A1	0.10	0.20	0.15			
b	0.30	0.50	0.40			
С	0.15	0.25	0.20			
D	4.85	4.95	4.90			
E	5.90	6.10	6.00			
E1	3.80	3.90	3.85			
E0	3.85	3.95	3.90			
е			1.27			
h	-		0.35			
L	0.62	0.82	0.72			
Q	0.60	0.70	0.65			
All	All Dimensions in mm					

Suggested Pad Layout

Please see http://www.diodes.com/package-outlines.html for the latest version.

SO-8



Dimensions	Value (in mm)			
С	1.27			
X	0.802			
X1	4.612			
Y	1.505			
Y1	6.50			



IMPORTANT NOTICE

- 1. DIODES INCORPORATED (Diodes) AND ITS SUBSIDIARIES MAKE NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARDS TO ANY INFORMATION CONTAINED IN THIS DOCUMENT, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION).
- 2. The Information contained herein is for informational purpose only and is provided only to illustrate the operation of Diodes' products described herein and application examples. Diodes does not assume any liability arising out of the application or use of this document or any product described herein. This document is intended for skilled and technically trained engineering customers and users who design with Diodes' products. Diodes' products may be used to facilitate safety-related applications; however, in all instances customers and users are responsible for (a) selecting the appropriate Diodes products for their applications, (b) evaluating the suitability of Diodes' products for their intended applications, (c) ensuring their applications, which incorporate Diodes' products, comply the applicable legal and regulatory requirements as well as safety and functional-safety related standards, and (d) ensuring they design with appropriate safeguards (including testing, validation, quality control techniques, redundancy, malfunction prevention, and appropriate treatment for aging degradation) to minimize the risks associated with their applications.
- 3. Diodes assumes no liability for any application-related information, support, assistance or feedback that may be provided by Diodes from time to time. Any customer or user of this document or products described herein will assume all risks and liabilities associated with such use, and will hold Diodes and all companies whose products are represented herein or on Diodes' websites, harmless against all damages and liabilities.
- 4. Products described herein may be covered by one or more United States, international or foreign patents and pending patent applications. Product names and markings noted herein may also be covered by one or more United States, international or foreign trademarks and trademark applications. Diodes does not convey any license under any of its intellectual property rights or the rights of any third parties (including third parties whose products and services may be described in this document or on Diodes' website) under this document.
- 5. Diodes' products are provided subject to Diodes' Standard Terms and Conditions of Sale (https://www.diodes.com/about/company/terms-and-conditions/terms-and-conditions-of-sales/) or other applicable terms. This document does not alter or expand the applicable warranties provided by Diodes. Diodes does not warrant or accept any liability whatsoever in respect of any products purchased through unauthorized sales channel.
- 6. Diodes' products and technology may not be used for or incorporated into any products or systems whose manufacture, use or sale is prohibited under any applicable laws and regulations. Should customers or users use Diodes' products in contravention of any applicable laws or regulations, or for any unintended or unauthorized application, customers and users will (a) be solely responsible for any damages, losses or penalties arising in connection therewith or as a result thereof, and (b) indemnify and hold Diodes and its representatives and agents harmless against any and all claims, damages, expenses, and attorney fees arising out of, directly or indirectly, any claim relating to any noncompliance with the applicable laws and regulations, as well as any unintended or unauthorized application.
- 7. While efforts have been made to ensure the information contained in this document is accurate, complete and current, it may contain technical inaccuracies, omissions and typographical errors. Diodes does not warrant that information contained in this document is error-free and Diodes is under no obligation to update or otherwise correct this information. Notwithstanding the foregoing, Diodes reserves the right to make modifications, enhancements, improvements, corrections or other changes without further notice to this document and any product described herein. This document is written in English but may be translated into multiple languages for reference. Only the English version of this document is the final and determinative format released by Diodes.
- 8. Any unauthorized copying, modification, distribution, transmission, display or other use of this document (or any portion hereof) is prohibited. Diodes assumes no responsibility for any losses incurred by the customers or users or any third parties arising from any such unauthorized use.
- 9. This Notice may be periodically updated with the most recent version available at https://www.diodes.com/about/company/terms-and-conditions/important-notice

DIODES is a trademark of Diodes Incorporated in the United States and other countries. The Diodes logo is a registered trademark of Diodes Incorporated in the United States and other countries. © 2022 Diodes Incorporated. All Rights Reserved.

www.diodes.com