High Power Silicon PIN Diodes



Silicon PIN Diode Chips

Rev. V2

Features

- Voltage Breakdown up to 800 V
- Passivated Mesa Construction
- Screening Available per MIL-PRF-19500 / 38534

Description

These silicon PIN diodes feature fully passivated mesa designs with tri-metalization for reliable operation under the most demanding conditions.



Electrical Specifications: $T_A = +25^{\circ}C$ (unless otherwise specified)

Part #	Breakdown Voltage V _B I _R = 10 µA	Series Resistance R _S I _F = 100 mA (100 MHz)	Junction Capacitance C _J V _R = 50 V	$\begin{array}{l} \mbox{Minority}\\ \mbox{Carrier}\\ \mbox{Lifetime}\\ \mbox{I}_{\rm F} = 10\mbox{ mA}\\ \mbox{I}_{\rm R} = 6\mbox{ mA}\\ \mbox{50\% recovery} \end{array}$	Theta	I-Region Width	Contact Diameter	Chip Size
	V	Ω	pF	ns	°C/W	μm	mils	Mils (sq.)
	Min.	Max.	Max.	Min.	Max.		Nominal	
MPN7330	300	0.5	0.40	500	10	30	10	15
MPN7360	600	0.4	1.00	2500	7	70	20	37
MPN7370	700	0.3	2.30	5000	5	70	40	64
MPN7380	800	0.5	0.60	2500	7	80	24	37
MPN7420	400	1.5	0.08	1000	30	100	5	15
MPN7453A-C12*	300	1.0	0.15	700	20	60	5	15
MPN7453B	400	0.9	0.20	2500	20	60	8	20
MPN7453C	300	0.7	0.25	1000	15	60	8	20

* - C12 Die Thickness = 6 - 9 mils.

MACOM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit <u>www.macom.com</u> for additional data sheets and product information.



Silicon PIN Diode Chips

Rev. V2

Absolute Maximum Ratings^{1,2}

Parameter	Absolute Maximum			
Power Dissipation (P _{DISS})	$P_{\text{DISS}} = \frac{175^{\circ}\text{C} - \text{T}_{c}}{\text{Thermal Resistance }\theta_{JC}}$			
Reverse Voltage	Rated V _{BR}			
Junction Temperature	+175°C			
Storage Temperature	-65°C to +200°C			

1. Exceeding any one or combination of these limits may cause permanent damage to this device.

MACOM does not recommend sustained operation near these survivability limits.

Handling Procedures

Please observe the following precautions to avoid damage:

Static Sensitivity

These electronic devices are sensitive to electrostatic discharge (ESD) and can be damaged by static electricity. Proper ESD control techniques should be used when handling these devices.





Figure 1.

Series Resistance vs. Forward Current



Figure 2.

Series Resistance vs. Forward Current



MACOM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit <u>www.macom.com</u> for additional data sheets and product information.

²



Silicon PIN Diode Chips Rev. V2

MACOM Technology Solutions Inc. ("MACOM"). All rights reserved.

These materials are provided in connection with MACOM's products as a service to its customers and may be used for informational purposes only. Except as provided in its Terms and Conditions of Sale or any separate agreement, MACOM assumes no liability or responsibility whatsoever, including for (i) errors or omissions in these materials; (ii) failure to update these materials; or (iii) conflicts or incompatibilities arising from future changes to specifications and product descriptions, which MACOM may make at any time, without notice. These materials grant no license, express or implied, to any intellectual property rights.

THESE MATERIALS ARE PROVIDED "AS IS" WITH NO WARRANTY OR LIABILITY, EXPRESS OR IMPLIED, RELATING TO SALE AND/OR USE OF MACOM PRODUCTS INCLUDING FITNESS FOR A PARTICULAR PURPOSE, MERCHANTABILITY, INFRINGEMENT OF INTELLECTUAL PROPERTY RIGHT, ACCURACY OR COMPLETENESS, OR SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES WHICH MAY RESULT FROM USE OF THESE MATERIALS.

MACOM products are not intended for use in medical, lifesaving or life sustaining applications. MACOM customers using or selling MACOM products for use in such applications do so at their own risk and agree to fully indemnify MACOM for any damages resulting from such improper use or sale.

³

MACOM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit <u>www.macom.com</u> for additional data sheets and product information.