Non-indicating Pressure Transmitters

Features

- Robust build allows high or low pressure measurement in high and low temperature environments.
 : high pressure (0 to 60MPa), low pressure (0 to 2 MPa)
- temperature range (-40 to 125°C) (may vary by model)
 For diverse applications including packaging machines, heavy
- For diverse applications including packaging machines, heavy machinery, factories, and shipbuilding.
- Pressure measurement of any gas, liquid, or oil.
- 316L stainless steel diaphragm for high corrosion resistance.
- Compact size allows easy installation in tight or limited spaces.
- 1ms high-speed response rate.
- · Analog output: Voltage (1-5 VDC), Current (DC 4-20 mA)
- · Built-in reverse polarity protection circuit.
- Various connector types
 : cable type, DIN43650-A connector type, DT04-3P connector type, M12 connector type, head type.

Example of External Connections

- Available thread sizes: G3/8, G1/4, R1/2
- Protection structure: IP67 (IEC standard) (except DIN43650-A connector type: IP65)

Please read "Safety Considerations" in the instruction manual before using



Cable type DIN43650-A connector type

DT04-3P M12 connector type type

Head type or



CE

0 2 3 4) (5 (
	Descriptio	n					
①Item	TPS30	Non-indicating Pressure Transmitt	ers				
	G	Gauge pressure, sealed gauge pre					
②Measurement pressure	A	Absolute pressure					
	1	Head type					
	2	DIN43650-A connector type					
③Cable	3	M12 connector type					
	4	DT04-3P connector type					
	5	Cable type					
		Gauge pressure	Absolute pressure				
	3	0 to 0.1MPa	0 to 0.1MPa				
	4	0 to 0.2MPa	0 to 0.2MPa				
	5	0 to 0.7MPa	0 to 0.7MPa				
	6	0 to 1MPa	0 to 1MPa				
	7	0 to 2MPa	0 to 2MPa				
	8 ^{**} 2	0 to 3.5MPa					
	9 ^{×2}	0 to 5MPa					
	A ^{⊗2}	0 to 10MPa					
	B ^{≈2}	0 to 20MPa	—				
④Pressure range	C ^{**2}	0 to 40MPa					
	D ^{%2}	0 to 50MPa					
	E ^{**2}	0 to 60MPa					
		Sealed gauge pressure ^{®1}					
	F	-0.1 to 0MPa					
	G	-0.1 to 0.1MPa					
	Н	-0.1 to 0.7MPa					
	J	-0.1 to 1MPa					
	K	-0.1 to 2MPa					
	Z	Others					
⑤Output type	V	Voltage (1-5VDC) output					
	A	Current (DC4-20mA) output					
	G8	G3/8 (PF)(EN387)					
	G4	G1/4 (PF)(EN387)					
	R2	R1/2 (PT)(DIN3852)					
	N4	NPT1/4 (DIN3852)					
	ZZ ^{×3}	Others (option)					
	00	Not used					
Dation	21	"I" type 2m					
⑦Option (connector cable) ^{≋4}	2L	"L" type 2m					
	51	"I" type 5m					
	5L	"L" type 5m					
⑧User pressure range		User pressure range ^{×⁵}					

Ordering Information

G8

00

(0 to 0.5MPa)

TPS30 - G 2 9 V

X1: The pressure is sealed gauge pressure. The unit is sealed structure. It is based on atmospheric pressure 101.3kPa (1.013bar).

2: G1/4 is the standard pressure port. For the other pressure ranges, G3/8, R1/2 are standard pressure ports.

※3: The option ports are sold separately. In case of large amount ordering, contact the Autonics for manufacturing the requested pressure port. %4: Only for M12 connector type.

*5: Write the desired pressure range and it is the default of user pressure range. (select "Z" at @Pressure range)

Specifications

Serie	s		TPS3																
Press	sure type			Gauge pressure, absolute pressure				Sealed gauge pressure ^{×1}			Gaug	Gauge pressure							
Rate	d pressure ranç	ge (MPa)	0 to 0.1	0 to 0.2	0 to 0.7	0 to 1	0 to 2	-0.1 to 0	-0.1 to 0.1	-0.1 to 0.7	-0.1 to 1	-0.1 to 2	0 to 3.5	0 to 5	0 to 10	0 to 20	0 to 40	0 to 50	0 to 60
	nded analog o e (MPa)	utput	0 to 0.11	0 to 0.22	0 to 0.77	0 to 1.1	0 to 2.2	-0.1 to 0.01	-0.1 to 0.12	-0.1 to 0.78	-0.1 to 1.11	-0.1 to 2.21	0 to 3.85	0 to 5.5	0 to 11	0 to 22	0 to 44	0 to 55	0 to 66
Max.	pressure rang	e (MPa)	0.6	0.6	3	3	3	0.6	0.6	3	3	3	10	20	50	80	120	120	120
	pressure (MP	/	0.6	0.6	3	3	3	0.6	0.6	3	3	3	15	30	75	120	160	160	160
Meas	ured materials											tainles	s stee	316L)					
Powe	er supply		• Curr	age out ent out	put typ	e: 11-3	36VDC												
Perm	issible voltage	range	90 to	110% c	of rated	voltag	е												
Curre consi	ent umption		• Volta	age out	put typ	e: max	k. 20m	A • (Current	output	type: ı	max. 3	0mA						
Resp	onse time		Max.	1ms															
	ction circuit			se pola															
<u> </u>	ut type		• Volta	age out	put typ	e: 1-5	VDC	• (Current	t outpu	t type:	DC4-2	0mA						
temp	pensation erature		-10 to 80°C 0 to 80°C																
Accu						ncludin	g linea	arity, hy	steres	is, rep	roducik	oility)							
	inearity Max. ±0.2% F.S.																		
Hysteresis Max. ±0.2% F.S.																			
	. Zero Shift					<u> </u>					/10°C (
<u> </u>	. Span Shift		Max. :	±0.1%	F.S./10	°C (sta	indard), max.	±0.25	% F.S.	/10°C (max.)	0.5.1	40.000					
Temperature characteristics			-25 to 100°C: max. ±1.5% F.S. -40 to 125°C: max. ±2.5% F.S.																
Load resistance			Current output type: max. 700Ω (supplying 24VDC)																
Dielectric strength			500VAC 50/60Hz for 1 minute																
Insula	ation ance		Over '	100MΩ	(at 50	OVDC	megge	er)											
Voltage		output	 Head type, DIN43650-A connector type, M12 connector type, DT04-3P connector type: -40 to 125°C, storage: -40 to 125°C Cable type: -40 to 80°C, storage: -40 to 80°C Head type, DIN43650-A connector type, M12 connector type, DT04-3P connector type: -40 to 85°C. 																
Environment		Current output	storage: -40 to 125°C - Cable type: -40 to 80°C, storage: -40 to 80°C																
ш	Ambient humi	idity	35 to	85%RI	1														
	Fluid temp.		-40 to 125°C																
Vibra			10g, 20 to 2,000Hz 20g, 20 to 2,000Hz																
Shoc			100g/6ms 500g/1ms																
	ening torque			10N·m															
Protection structure			Head type, M12 connector type, DT04-3P connector type, cable type: IP67 (IEC standard) DIN43650-A connector type: IP65 (IEC standard)																
Mate	rial			ess ste water-p				art of head type: aluminium diecasting), connector: polybutylene terephthalate :on											
	ection			age ou	tput ty	oe: +, -	, Vout	۰Cu	rrent o	utput t	ype: +,	-							
Appro Weig			• DIN4		A conn	ector t	ype, M	12 con	nector	type,	DT04-3	3P con	nector	type: a	pprox.	130g	(appro	x. 50g)	
			l·Cap	le type	. appro	vx. ∠00	y (app	10X. 12	.ug)										

X1: The sensor is sealed structure. It is based on atmospheric pressure 101.3kPa (1.013bar).

X2: The weight includes packaging. The weight in parenthesis is for unit only.

XEnvironment resistance is rated at no freezing or condensation.

Dimensions

• Head type

(unit: mm)



• DIN43650-A connector type







• M12 connector type







• DT04-3P connector type







Connector: CS-DT3P, sold separately

Dimensions

(unit: mm)



Connection Cable (Sold Separately)

• CID3-2/CID3-5



(unit: mm)

Model	L(m)	Material
CID3-2	2	PVC
CID3-5	5	PVC

XOnly for M12 connector.

CLD3-2/CLD3-5



Model	L(m)	Material
CLD3-2	2	PVC
CLD3-5	5	FVC

Connectors

• Voltage output type

	Head type	DIN43650-A connector type	M12 connector type	DT04-3P connector type	Cable type
Pin type	VCC GND Vout				Brown Black Blue
Func.	Pin				
+	+	1	1	A	Brown
-	-	(3	С	Blue
Vout	Vout	2	4	В	Black
N·C		3	2	—	_

• Current output type

	Head type	DIN43650-A connector type	M12 connector type	DT04-3P connector type	Cable type
Pin type	VCC GND Vout				Brown
Func.	Pin				
+	+	1	1	А	Brown
-	-	(3	С	Blue
N·C	Vout	2, 3	2, 4	В	—



Connections



(brown) VCC LOAD Main Circuit 11-36VDC Current amplifier (blue) GND

%Cable color is only for cable type.

Troubleshooting

Error	Troubleshooting
No outputs	Check the power supply. Check the polarity (+, -) when wiring the cable. Check the connection part.
Abnormally fluctuating output	Check the power supply. Check the supplied pressure. Check the pressure line.
Out of zero point output value	Check the power supply. Check the load resistive value of current output type for a receiver is over 700Ω . (when supplying 24VDC) Check the measuring point and transmission distance. Check the line resistance is below 700Ω .

Proper Usage

- · Follow instructions in 'Cautions during Use'. Otherwise, It may cause unexpected accidents.
- 8-36VDC, 11-36VDC power supply should be insulated and limited voltage/current or Class 2, SELV power supply device.
- When installing the unit on pipe line, use the hexagon part of connections not to turn the unit with a pipe wrench. Do not use the unit with strong vibrations.
- Store the unit at the place without moisture, dust, and vibration.
- This product which does not have drive part at sensing part does not need to repair it. Even though inside of pressure pipe is normally clean, it needs to take maintenance once a year as below instructions.
 - (1) Check the broken status of outside.
 - 2 Check the pressure slot, cleanliness inside, and corrosion state.
 - ③ Short each terminal and check the insulation resistance between the case and power.
- · When removing a sensor for maintenance, follow the below instructions.
 - ①Replace an O-ring which is used once.

^②Be sure that diaphragm part is not damaged.

- Switch or circuit breaker for suppling or cutting off the power should be installed nearby users for convenient control.
- The unit cannot be repaired due to disassembled structure.
- The unit is fixed with bolt and nut at the both sides of case.
 Do not press excessive load (approx. 300kg/cm²), or it may cause damage to the unit.
- This unit may be used in the following environments.
 - ① Indoor / Outdoor (in the environment condition rated in 'Specifications')
 - 2 Altitude max. 2,000 m
 - ③ Pollution Degree 2
 - (4) Installation Category II